

Syncro

Analogue Addressable 6 or 8 Loop Control Panels

Features

- 6 or 8 loop versions as standard
- 96 zone indicators
- Fully supports Apollo, Argus Vega & Hochiki protocols
- Network up to 32 6 or 8 loop panels
- 8 programmable sounder circuits as standard
- 2 x 5.25 amp PSU's to EN54 part 4
- Large graphic display
- In built help and alarm information screens
- Complies with EN54-2/4
- Real time clock
- Supports Apollo, Argus Vega and Hochiki loop powered sounders and beacons
- Stylish enclosure design
- Soft-touch tactile buttons
- 2 programmable function buttons
- 3 programmable front panel mounted LED's
- Improved Front loading Printer (optional)
- Up to 1024 programmable inputs/outputs per panel via 2 wire RS485 serial link (optional)
- Simple Windows® graphical configuration utility
- Wide choice of languages available

 explorer

(Also backward-compatible with Series 90 detectors)

 XP95

 DISCOVERY

 ARGUS SECURITY

 series90

 HOCHIKI RSP COMPATIBLE

Product Overview

- Available with 6 or 8 detection circuits, each capable of hosting up to 126 devices (Apollo), 240 devices (Argus Vega) or 127 devices (Hochiki). Syncro uses the most advanced microprocessor technology to provide a control system of extremely high integrity.
- Syncro can be configured to suit all types of system, from the most simple, to the highly complex. Its fully integrated and secure network provides comprehensive scalability.
- A large area graphic display ensures that information is presented in plain language with detailed extra help available by pressing a 'help' button.
- Syncro supports three of the most widely used communication protocols produced by leading fire detector manufacturers and employs daily calibration routines to ensure that the system is always at optimum performance.

Config. Features

- Comprehensive day/night mode facility
- Programmable one touch test mode
- Powerful and versatile cause & effect programming
- Cause & effect wizard including:
 - Cause & effect action
 - Disablement configuration
 - Test mode configuration



Model No. EN#63966S4P

Panels

Product Code	Loops	Enable Control	Zones	Size (mm)
EN#63966S4	6	No	96	570W x 420H x 155D
ENS#63966S4	6	Yes	96	570W x 420H x 155D
EN#63968S4	8	No	96	570W x 420H x 155D
ENS#63968S4	8	Yes	96	570W x 420H x 155D

`#` - replace with `A` for Apollo protocol,

`V` for Argus Vega protocol or `H` for Hochiki protocol.

For fitted printer add `P` after stock code.

Options

Product Code Description

K552#	Loop extension card (loops 7 & 8)
K768SYN	Thermal printer kit (for retrofitting to non-printer models)
K560	16 channel input/output board
K547	8 way relay extender board
K546	6 way sounder extender board
K545	4 way conventional detection zone board
K556P	Modem module (PSTN)
B3472	Thermal Paper Printer Roll

`#` - replace with `A` for Apollo protocol,

`V` for Argus Vega protocol or `H` for Hochiki protocol.



Technical

Construction	- 1.2mm mild sheet steel
IP Rating	- IP30
Finish	- Epoxy powder coated
Colour - lid & box	- BS 00 A 05 grey - fine texture
Colour - controls plate & labels	- RAL 7047 light grey - satin
Weight	- 18kg (standard panel)
Display	- 8 lines of 40 characters graphic LCD
Detection circuits (Loops)	- 6 or 8 (400mA each)
Zone LED's	- 96 (up to 500 software zones)
8 sounder circuits	- Each fused at 1 Amp (total load 2 Amp per bank of 4 circuits)
2 x Fire contact	- Volt free 1 Amp 30V DC
2 x Alarm contact	- Volt free 1 Amp 30V DC
2 x Fault contact	- Volt free 1 Amp 30V DC
2 x Programmable relay 1	- Volt free 1 Amp 30V DC
2 x Programmable relay 2	- Volt free 1 Amp 30V DC
2 x Fire routing output	- Monitored-voltage reversing, fused at 500mA
2 x Fault routing output	- Monitored-voltage reversing, fused at 500mA
2 x Extinguisher output	- Monitored-voltage reversing, fused at 1A
2 x Fault input	- Volt free contact input signals fault
2 x Reset input	- Volt free contact input resets panel
2 x Intermittent input	- Volt free contact input pulses sounder outputs
2 x Continuous input	- Volt free contact input for continuous sounders
2 x Silence input	- Volt free contact input silences sounders
2 x Programmable input 1	- Volt free contact for any action required
2 x Programmable input 2	- Volt free contact for any action required
2 x Programmable input 3	- Volt free contact for any action required
2 x Auxiliary 24V DC output	- Fused at 500mA
2 x System fuse	- 5 Amp self-resetting polyfuse
2 x Mains fuse	- 20mm 3 Amp
Operating Temperature	- -5 to +50 deg. C
Operating humidity	- To 95% (non-condensing)
Mains voltage supply	- 110 or 230V AC 50 or 60 Hz. (specify when ordering, default is 230V)
Battery (24 hour standby)	- 12Ah 12V (4 per panel)
Day/night modes	- 2 with variable device sensitivity
Input delays	- Individual for each device selectable up to 2 minutes
Output delays	- Individual 2-stage to 10 minutes per stage
2 programmable function buttons	- Programmable to carry out any cause & effect, disablement or test action
3 programmable indicators	- Red/yellow/green to indicate any action
Network	- Up to 32 6 or 8 loop panels on 2 wires
Printer (option)	- New front loading feature
Download lead	- S187 (standard) or X187LS (economy)